



ClareOne Keyfob

CLR-C1-KF

Panic



The ClareOne Keyfob places on-the-go arm/disarm control of the ClareOne Panel in a familiar form-factor that fits the user's hand and key ring. By pressing the SOS button, this battery-operated wireless handheld can also be used to activate a panic or life-safety alarm with the central monitoring station.

Specifications

Compatible panel	ClareOne (CLR-C1-PNL1)
Transmitter frequency	433MHz
Encrypted	Yes
Transmitted indications	Low battery
Buttons	4 Buttons: Stay, Away, Disarm, SOS
LED indication	1 LED (blue)
Battery type	CR2032
Battery life	Up to 5 years
Operating temperature	32 to 122.6°F (0 to 50°C)
Relative humidity	85% max
Dimensions (W x H x D)	1.49 x 2.53 x .55 in. (38 x 64.5 x 14 mm)
Water resistant	IPX4
Certifications	FCC: 15.109 Class B 15.231, Industry Canada: ICES-003, RSS-210, ETL listed to: UL-1023 and ULC-C1023

*The ClareOne Keyfob must be within range of the ClareOne panel to function properly.

Performance Highlights:

- Can be attached to any key ring
- Communicate with the panel to set arm away, arm stay, disarm, or panic states
- Long lasting battery life
- Encrypted technology prevents device takeovers
- Pairs easily and quickly with the ClareOne panel

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, wireless security, controllable lighting, and IP CCTV components. For more information, visit clarecontrols.com.