



Clare Pet Immune PIR Motion Sensor

CS-PIR-10



This wall-mountable, battery-operated sensor is immune to pet activity and will last 6-8 years on one battery. It's discrete size and form factor allow for mounting virtually anywhere in the home.

- Industry-leading pet immunity
- Supports both motion zone and an external contact zone
- Wireless connection to security panel

Technical Specifications	
General	
Dimensions	3.50 x 2.40 x 1.70" (8.9 x 6.1 x 4.3cm)
Weight (with battery)	3.2oz (91 grams)
Mounting Fastener	Double sided tape or screws (both provided)
Environmental	
Operating Temperature	32° to 120°F (0 to 49°C)
Maximum Humidity	85% non-condensing relative humidity
Sensor Specifications	
Frequency	433.92 MHz
Pet Immunity	Two 60lb dogs or one 85lb dog
Replacement Battery	One Panasonic CR132A
Nominal Battery Life	6 to 8 years
Current Draw	30 mA (maximum), 20 uA (quiescent)
Optimal Mounting Height	
optimal Mounting Height	7.5 to 9.5ft (2.3 to 3.0m)
Transmitted Indications	7.5 to 9.5ft (2.3 to 3.0m) Cover tamper, low battery, supervision
	, ,
Transmitted Indications	, ,
Transmitted Indications Certification	Cover tamper, low battery, supervision